

BV030-7312.0 Information

Heisener.com

Part Number BV030-7312.0

Manufacturer Pulse Electronics Power

Category Transformers

Power Transformers

Description XFRMR LAMINATED 2VA THRU HOLE

Package

For the pricing/inventory/lead time, please contact

Website: https://www.heisener.com For Reference Only

E-mail: salesdept@heisener.com



Request a Quote

Certified Quality

Heisener's commitment to quality has shaped our processes for sourcing, testing, shipping, and every step in between. This foundation underlies each component we sell.









BV030-7312.0 Specifications

Manufacturer Part NumberBV030-7312.0ManufacturerPulse Electronics PowerCategoryTransformersPower TransformersPower TransformersPackage-Series-TypeLaminated CoreVoltage - Primary230VVoltage - Secondary (Full Load)Parallel 12V, Series 24VCurrent - Output (Max)Parallel 166mA, Series 83mAPrimary Winding(s)SingleSecondary Winding(s)DualCenter TapNoPower - Max2 VAMounting TypeThrough Hole
Category Transformers Power Transformers Package Series Type Laminated Core Voltage - Primary Voltage - Secondary (Full Load) Parallel 12V, Series 24V Current - Output (Max) Primary Winding(s) Secondary Winding(s) Secondary Winding(s) Center Tap Power - Max Primary Wanding(s) Parallel 166mA, Series 83mA No Parallel 166mA, Series 83mA Primary Winding(s) Single Secondary Winding(s) Dual Center Tap No 2 VA
Package - Series - Type Laminated Core Voltage - Primary 230V Voltage - Secondary (Full Load) Parallel 12V, Series 24V Current - Output (Max) Parallel 166mA, Series 83mA Primary Winding(s) Single Secondary Winding(s) Dual Center Tap No Power - Max 2 VA
Package - Series - Laminated Core Type Laminated Core Voltage - Primary 230V Voltage - Secondary (Full Load) Parallel 12V, Series 24V Current - Output (Max) Parallel 166mA, Series 83mA Primary Winding(s) Single Secondary Winding(s) Dual Center Tap No Power - Max 2 VA
Series - Type Laminated Core Voltage - Primary 230V Voltage - Secondary (Full Load) Parallel 12V, Series 24V Current - Output (Max) Parallel 166mA, Series 83mA Primary Winding(s) Single Secondary Winding(s) Dual Center Tap No Power - Max 2 VA
Type Voltage - Primary 230V Voltage - Secondary (Full Load) Parallel 12V, Series 24V Current - Output (Max) Primary Winding(s) Secondary Winding(s) Dual Center Tap No Power - Max Laminated Core 230V Parallel 12V, Series 24V Parallel 166mA, Series 83mA Primary Winding(s) Single Dual Center Tap No
Voltage - Primary Voltage - Secondary (Full Load) Current - Output (Max) Primary Winding(s) Secondary Winding(s) Center Tap Power - Max Poltage - Primary 230V Parallel 12V, Series 24V Parallel 166mA, Series 83mA Single Dual Center Tap No 2 VA
Voltage - Secondary (Full Load) Current - Output (Max) Primary Winding(s) Secondary Winding(s) Center Tap Power - Max Parallel 12V, Series 24V Parallel 166mA, Series 83mA Single Dual Voltage - Secondary Winding(s) Dual
Current - Output (Max) Primary Winding(s) Secondary Winding(s) Center Tap No Power - Max Parallel 166mA, Series 83mA Single Dual Cylindric No 2 VA
Primary Winding(s) Secondary Winding(s) Dual Center Tap No Power - Max 2 VA
Secondary Winding(s) Center Tap No Power - Max Dual No 2 VA
Center Tap No Power - Max 2 VA
Power - Max 2 VA
Mounting Type Through Hole
111045111010
Termination Style PC Pin
Size / Dimension 32.50mm L x 27.50mm W
Height - Seated (Max) 27.00mm
Voltage - Isolation -
Weight 0.133 lb (60.33g)
Report errors

BV030-7312.0 Guarantees



Quality Guarantees

We provide 90 days warranty. *

If the items you received were not in perfect quality, we would be responsible for your refund or replacement, but the items must be returned in their original condition.



Service Guarantees

We guarantee 100% customer satisfaction.

Our experienced sales team and tech support team back our services to satisfy all our customers.

BV030-7312.0 Payment Methods



















BV030-7312.0 Shipping Methods













If you have any question about BV030-7312.0, please do not hesitate to contact us!

Website: https://www.heisener.com E-mail: salesdept@heisener.com