



OP07EP Information



For Reference Only

Part Number OP07EP

Manufacturer Maxim Integrated

Category Integrated Circuits (ICs)

Linear - Amplifiers - Instrumentation, OP Amps,

Buffer Amps

Description IC OPAMP GP 600KHZ 8DIP

Package 8-DIP (0.300", 7.62mm)

For the pricing/inventory/lead time, please contact

us

Website: https://www.heisener.com E-mail: salesdept@heisener.com



Request a Quote

Certified Quality

Heisener's commitment to quality has shaped our processes for sourcing, testing, shipping, and every step in between. This foundation underlies each component we sell.









OP07EP Specifications

| Manufacturer Part Number OP07EP Manufacturer Maxim Integrated Category Integrated Circuits (ICs) Linear - Amplifiers - Instrumentation, OP Amps, Buffer Amps Package 8-DIP (0.300", 7.62mm) Series - Amplifier Type General Purpose Number of Circuits 1 Output Type - Slew Rate 0.3 V/μs Gain Bandwidth Product 600kHz -3db Bandwidth - Current - Input Bias 1.2nA Voltage - Input Offset 30μV | |
|---|------|
| Category Integrated Circuits (ICs) Linear - Amplifiers - Instrumentation, OP Amps, Buffer Amps Package 8-DIP (0.300", 7.62mm) Series - Amplifier Type General Purpose Number of Circuits 1 Output Type - Slew Rate 0.3 V/μs Gain Bandwidth Product 600kHz -3db Bandwidth - Current - Input Bias 1.2nA Voltage - Input Offset 30μV | |
| Linear - Amplifiers - Instrumentation, OP Amps, Buffer Amps Package 8-DIP (0.300", 7.62mm) Series - Amplifier Type General Purpose Number of Circuits 1 Output Type - Slew Rate 0.3 V/μs Gain Bandwidth Product 600kHz -3db Bandwidth - Current - Input Bias 1.2nA Voltage - Input Offset 30μV | |
| Package 8-DIP (0.300", 7.62mm) Series - Amplifier Type General Purpose Number of Circuits 1 Output Type - Slew Rate 0.3 V/μs Gain Bandwidth Product 600kHz -3db Bandwidth - Current - Input Bias 1.2nA Voltage - Input Offset 30μV | |
| Series - Amplifier Type General Purpose Number of Circuits 1 Output Type - Slew Rate 0.3 V/μs Gain Bandwidth Product 600kHz -3db Bandwidth - Current - Input Bias 1.2nA Voltage - Input Offset 30μV | |
| Amplifier Type General Purpose Number of Circuits 1 Output Type - Slew Rate 0.3 V/μs Gain Bandwidth Product 600kHz -3db Bandwidth - Current - Input Bias 1.2nA Voltage - Input Offset 30μV | |
| Number of Circuits 1 Output Type - Slew Rate 0.3 V/ μ s Gain Bandwidth Product 600kHz -3db Bandwidth - Current - Input Bias 1.2nA Voltage - Input Offset 30 μ V | |
| Output Type Slew Rate 0.3 V/µs Gain Bandwidth Product 600kHz -3db Bandwidth Current - Input Bias 1.2nA Voltage - Input Offset 30µV | |
| Slew Rate 0.3 V/ μ s Gain Bandwidth Product 600kHz -3db Bandwidth - Current - Input Bias 1.2nA Voltage - Input Offset 30 μ V | |
| Gain Bandwidth Product -3db Bandwidth - Current - Input Bias 1.2nA Voltage - Input Offset 30μV | |
| -3db Bandwidth - Current - Input Bias 1.2nA Voltage - Input Offset 30μV | |
| Current - Input Bias 1.2nA Voltage - Input Offset 30μV | |
| Voltage - Input Offset 30μV | |
| | |
| Current Cumly | |
| Current - Supply - | |
| Current - Output / Channel - | |
| Voltage - Supply, Single/Dual (\pm) $\pm 3 \text{ V} \sim 18 \text{ V}$ | |
| Operating Temperature $0^{\circ}\text{C} \sim 70^{\circ}\text{C}$ | |
| Mounting Type Through Hole | |
| Package / Case 8-DIP (0.300", 7.62mm) | |
| Supplier Device Package 8-PDIP | |
| Report err | ors? |

OP07EP Guarantees



Quality Guarantees

We provide 90 days warranty. *

If the items you received were not in perfect quality, we would be responsible for your refund or replacement, but the items must be returned in their original condition.



Service Guarantees

We guarantee 100% customer satisfaction.

Our experienced sales team and tech support team back our services to satisfy all our customers.

OP07EP Payment Methods



















OP07EP Shipping Methods













If you have any question about OP07EP, please do not hesitate to contact us!

Website: https://www.heisener.com E-mail: salesdept@heisener.com