

## 3000MD-1-004 Information

Manufact Category

Part Number 3000MD-1-004

Manufacturer Talema Group LLC

Category Transformers

Power Transformers

**Description** XFMR TOROIDAL 3000VA THRM PROTCT

Package -

For the pricing/inventory/lead time, please contact

us

Website: https://www.heisener.com E-mail: salesdept@heisener.com



Request a Quote

## **Certified Quality**

For Reference Only

Heisener's commitment to quality has shaped our processes for sourcing, testing, shipping, and every step in between. This foundation underlies each component we sell.









# 3000MD-1-004 Specifications

Manufacturer Part Number3000MD-1-004ManufacturerTalema Group LLCCategoryTransformersPower TransformersPower TransformersPackage-SeriesMDTypeToroidalVoltage - Primary100V, 120V, 200V, 240VVoltage - Secondary (Full Load)Parallel 120V, Series 240VCurrent - Output (Max)Parallel 25A, Series 12.5APrimary Winding(s)Dual, Multiple TapsSecondary Winding(s)DualCenter TapNoPower - Max3000 VA
Category  Transformers  Power Transformers  Package  - Series  MD  Type  Toroidal  Voltage - Primary  100V, 120V, 200V, 240V  Voltage - Secondary (Full Load)  Parallel 120V, Series 240V  Current - Output (Max)  Parallel 25A, Series 12.5A  Primary Winding(s)  Dual, Multiple Taps  Secondary Winding(s)  Dual  Center Tap  No
Power Transformers  Package - Series MD  Type Toroidal  Voltage - Primary 100V, 120V, 200V, 240V  Voltage - Secondary (Full Load) Parallel 120V, Series 240V  Current - Output (Max) Parallel 25A, Series 12.5A  Primary Winding(s) Dual, Multiple Taps  Secondary Winding(s) Dual  Center Tap No
Package - Series MD  Type Toroidal  Voltage - Primary 100V, 120V, 200V, 240V  Voltage - Secondary (Full Load) Parallel 120V, Series 240V  Current - Output (Max) Parallel 25A, Series 12.5A  Primary Winding(s) Dual, Multiple Taps  Secondary Winding(s) Dual  Center Tap No
Series MD  Type Toroidal  Voltage - Primary 100V, 120V, 200V, 240V  Voltage - Secondary (Full Load) Parallel 120V, Series 240V  Current - Output (Max) Parallel 25A, Series 12.5A  Primary Winding(s) Dual, Multiple Taps  Secondary Winding(s) Dual  Center Tap No
Type Toroidal  Voltage - Primary 100V, 120V, 200V, 240V  Voltage - Secondary (Full Load) Parallel 120V, Series 240V  Current - Output (Max) Parallel 25A, Series 12.5A  Primary Winding(s) Dual, Multiple Taps  Secondary Winding(s) Dual  Center Tap No
Voltage - Primary  Voltage - Secondary (Full Load)  Parallel 120V, Series 240V  Current - Output (Max)  Parallel 25A, Series 12.5A  Primary Winding(s)  Dual, Multiple Taps  Secondary Winding(s)  Dual  Center Tap  No
Voltage - Secondary (Full Load)  Current - Output (Max)  Parallel 120V, Series 240V  Parallel 25A, Series 12.5A  Primary Winding(s)  Dual, Multiple Taps  Secondary Winding(s)  Dual  Center Tap  No
Current - Output (Max) Parallel 25A, Series 12.5A Primary Winding(s) Dual, Multiple Taps Secondary Winding(s) Dual Center Tap No
Primary Winding(s)  Secondary Winding(s)  Center Tap  Dual, Multiple Taps  Dual  No
Secondary Winding(s)  Center Tap  No
Center Tap No
-
Power - Max 3000 VA
Mounting Type Chassis Mount
Termination Style Wire Leads
Size / Dimension 265.00mm Dia x 120.00mm W
Height - Seated (Max)
Voltage - Isolation 5000Vrms
Weight 58 lbs (26.3kg)
Report errors?

### 3000MD-1-004 Guarantees



#### **Quality Guarantees**

We provide 90 days warranty. \*

If the items you received were not in perfect quality, we would be responsible for your refund or replacement, but the items must be returned in their original condition.



#### **Service Guarantees**

We guarantee 100% customer satisfaction.

Our experienced sales team and tech support team back our services to satisfy all our customers.

## 3000MD-1-004 Payment Methods



















## 3000MD-1-004 Shipping Methods













If you have any question about 3000MD-1-004, please do not hesitate to contact us!

Website: https://www.heisener.com E-mail: salesdept@heisener.com