

**3622C101KT Information**


For Reference Only

**Part Number** [3622C101KT](#)  
**Manufacturer** TE Connectivity Passive Product  
**Category** Inductors, Coils, Chokes  
[Fixed Inductors](#)  
**Description** FIXED IND 100UH 1.2A 330 MOHM  
**Package** Nonstandard  
 For the pricing/inventory/lead time, please contact us  
 Website: <https://www.heisener.com>  
 E-mail: [salesdept@heisener.com](mailto:salesdept@heisener.com)


[Request a Quote](#)
**Certified Quality**

Heisener's commitment to quality has shaped our processes for sourcing, testing, shipping, and every step in between. This foundation underlies each component we sell.


**3622C101KT Specifications**

Manufacturer Part Number	<a href="#">3622C101KT</a>
Manufacturer	TE Connectivity Passive Product
Category	Inductors, Coils, Chokes <a href="#">Fixed Inductors</a>
Package	Nonstandard
Series	3622, Sigma Inductors
Type	Wirewound
Material - Core	-
Inductance	100µH
Tolerance	±10%
Current Rating	1.2A
Current - Saturation	1A
Shielding	Unshielded
DC Resistance (DCR)	330 mOhm Max
Q @ Freq	-
Frequency - Self Resonant	8MHz
Ratings	-
Operating Temperature	-40°C ~ 105°C
Frequency - Test	100kHz
Features	-
Mounting Type	Surface Mount
Package / Case	Nonstandard
Supplier Device Package	-
Size / Dimension	0.500" L x 0.394" W (12.70mm x 10.00mm)

Height - Seated (Max)

0.197" (5.00mm)

[Report errors?](#)

### 3622C101KT Guarantees



#### Quality Guarantees

We provide 90 days warranty. \*

If the items you received were not in perfect quality, we would be responsible for your refund or replacement, but the items must be returned in their original condition.



#### Service Guarantees

We guarantee 100% customer satisfaction.

Our experienced sales team and tech support team back our services to satisfy all our customers.

### 3622C101KT Payment Methods



### 3622C101KT Shipping Methods



If you have any question about 3622C101KT, please do not hesitate to contact us!

Website: <https://www.heisener.com>

E-mail: [salesdept@heisener.com](mailto:salesdept@heisener.com)