

6534S-1-102

6534S-1-102 Information



| umber | 055151102 |
|----------|--|
| facturer | Bourns Inc. |
| ory | Potentiometers, Variable Resistors Rotary Potentiometers, Rheostats |
| iption | POT 1K OHM 1W PLASTIC LINEAR |
| ige | - |
| | For the pricing/inventory/lead time, please contact |
| | us |
| | Website: https://www.heisener.com |
| | E-mail: salesdept@heisener.com |
| | |



Request a Quote

Certified Quality

For Reference Only

Heisener's commitment to quality has shaped our processes for sourcing, testing, shipping, and every step in between. This foundation underlies each component we sell.



6534S-1-102 Specifications

| | (5248-1-102 |
|--------------------------|------------------------------------|
| Manufacturer Part Number | 6534S-1-102 |
| Manufacturer | Bourns Inc. |
| Category | Potentiometers, Variable Resistors |
| | Rotary Potentiometers, Rheostats |
| Package | - |
| Series | 6534 |
| Taper | Linear |
| Resistance (Ohms) | 1k |
| Tolerance | $\pm 10\%$ |
| Number of Gangs | 1 |
| Built in Switch | None |
| Power (Watts) | 1W |
| Temperature Coefficient | $\pm 500 ppm/^{\circ}C$ |
| Number of Turns | 1 |
| Rotation | Continuous |
| Adjustment Type | User Defined |
| Resistive Material | Conductive Plastic |
| Termination Style | Solder Turret |
| Actuator Type | Round |
| Actuator Length | 0.500" (12.70mm) |
| Actuator Diameter | 0.1248" (3.17mm) |
| Bushing Thread | - |
| Mounting Type | Servo Mount |
| | Report errors? |

6534S-1-102 Guarantees



Quality Guarantees

We provide 90 days warranty. * If the items you received were not in perfect quality, we would be responsible for your refund or replacement, but the items must be returned in their original condition.

SERVICE SUARANTEE

Service Guarantees

We guarantee 100% customer satisfaction. Our experienced sales team and tech support team back our services to satisfy all our customers.



If you have any question about 6534S-1-102, please do not hesitate to contact us! Website: https://www.heisener.com E-mail: salesdept@heisener.com