


**79FR18M Information**


For Reference Only

**Part Number** [79FR18M](#)  
**Manufacturer** Bourns Inc.  
**Category** Inductors, Coils, Chokes  
[Fixed Inductors](#)  
**Description** FIXED IND 180NH 600MA 240 MOHM  
**Package** Axial  
 For the pricing/inventory/lead time, please contact us  
 Website: <https://www.heisener.com>  
 E-mail: [salesdept@heisener.com](mailto:salesdept@heisener.com)


[Request a Quote](#)
**Certified Quality**

Heisener's commitment to quality has shaped our processes for sourcing, testing, shipping, and every step in between. This foundation underlies each component we sell.


**79FR18M Specifications**

Manufacturer Part Number	<a href="#">79FR18M</a>
Manufacturer	Bourns Inc.
Category	Inductors, Coils, Chokes <a href="#">Fixed Inductors</a>
Package	Axial
Series	79F
Type	Wirewound
Material - Core	Ferrite
Inductance	180nH
Tolerance	±20%
Current Rating	600mA
Current - Saturation	-
Shielding	Unshielded
DC Resistance (DCR)	240 mOhm Max
Q @ Freq	35 @ 25MHz
Frequency - Self Resonant	300MHz
Ratings	-
Operating Temperature	-55°C ~ 105°C
Frequency - Test	25MHz
Features	-
Mounting Type	Through Hole
Package / Case	Axial
Supplier Device Package	Axial
Size / Dimension	0.100" Dia x 0.160" L (2.54mm x 4.06mm)

## 79FR18M Guarantees



### Quality Guarantees

We provide 90 days warranty. \*

If the items you received were not in perfect quality, we would be responsible for your refund or replacement, but the items must be returned in their original condition.



### Service Guarantees

We guarantee 100% customer satisfaction.

Our experienced sales team and tech support team back our services to satisfy all our customers.

## 79FR18M Payment Methods



## 79FR18M Shipping Methods



If you have any question about 79FR18M, please do not hesitate to contact us!

Website: <https://www.heisener.com>

E-mail: [salesdept@heisener.com](mailto:salesdept@heisener.com)