

BA10358N Information



For Reference Only

Part Number BA10358N

Manufacturer Rohm Semiconductor

Category Integrated Circuits (ICs)

Linear - Amplifiers - Instrumentation, OP Amps,

Buffer Amps

Description IC OPAMP GP 500KHZ 8SIP

Package 8-SIP

For the pricing/inventory/lead time, please contact

us

Website: https://www.heisener.com E-mail: salesdept@heisener.com



Request a Quote

Certified Quality

Heisener's commitment to quality has shaped our processes for sourcing, testing, shipping, and every step in between. This foundation underlies each component we sell.









BA10358N Specifications

Manufacturer Part NumberBA10358NManufacturerRohm SemiconductorCategoryIntegrated Circuits (ICs)Linear - Amplifiers - Instrumentation, OP Amps, Buffer AmpsPackage8-SIPSeries-Amplifier TypeGeneral PurposeNumber of Circuits2Output Type-Slew Rate0.2 V/μsGain Bandwidth Product500kHz-3db Bandwidth-Current - Input Bias45nA	
Category Integrated Circuits (ICs) Linear - Amplifiers - Instrumentation, OP Amps, Buffer Amps Package 8-SIP Series - Amplifier Type General Purpose Number of Circuits 2 Output Type - Slew Rate 0.2 V/µs Gain Bandwidth Product -3db Bandwidth -	
Linear - Amplifiers - Instrumentation, OP Amps, Buffer Amps Package 8-SIP Series - Amplifier Type General Purpose Number of Circuits 2 Output Type - Slew Rate 0.2 V/μs Gain Bandwidth Product 500kHz -3db Bandwidth -	
Package8-SIPSeries-Amplifier TypeGeneral PurposeNumber of Circuits2Output Type-Slew Rate0.2 V/μsGain Bandwidth Product500kHz-3db Bandwidth-	
Series - Amplifier Type General Purpose Number of Circuits 2 Output Type - Slew Rate 0.2 V/μs Gain Bandwidth Product 500kHz -3db Bandwidth -	
Amplifier Type General Purpose Number of Circuits 2 Output Type - Slew Rate 0.2 V/µs Gain Bandwidth Product 500kHz -3db Bandwidth -	
Number of Circuits 2 Output Type - Slew Rate 0.2 V/μs Gain Bandwidth Product 500kHz -3db Bandwidth -	
Output Type - Slew Rate 0.2 V/µs Gain Bandwidth Product 500kHz -3db Bandwidth -	
Slew Rate 0.2 V/μs Gain Bandwidth Product 500kHz -3db Bandwidth -	
Gain Bandwidth Product 500kHz -3db Bandwidth -	
-3db Bandwidth -	
Current - Input Bias 45nA	
Current input blue	
Voltage - Input Offset 2mV	
Current - Supply 700µA	
Current - Output / Channel 20mA	
Voltage - Supply, Single/Dual (\pm) 3 V ~ 32 V, \pm 1.5 V ~ 16 V	
Operating Temperature $-40^{\circ}\text{C} \sim 85^{\circ}\text{C}$	
Mounting Type Through Hole	
Package / Case 8-SIP	
Supplier Device Package 8-SIP	
Report et	rrors?

BA10358N Guarantees



Quality Guarantees

We provide 90 days warranty. *

If the items you received were not in perfect quality, we would be responsible for your refund or replacement, but the items must be returned in their original condition.



Service Guarantees

We guarantee 100% customer satisfaction.

Our experienced sales team and tech support team back our services to satisfy all our customers.

BA10358N Payment Methods





















BA10358N Shipping Methods













If you have any question about BA10358N, please do not hesitate to contact us!

Website: https://www.heisener.com E-mail: salesdept@heisener.com