



### **ELJ-FB391KF Information**



For Reference Only

Part Number ELJ-FB391KF

Manufacturer Panasonic Electronic Components

Category Inductors, Coils, Chokes

**Fixed Inductors** 

**Description** FIXED IND 390UH 70MA 19 OHM SMD

Package 1812 (4532 Metric)

For the pricing/inventory/lead time, please contact

us

Website: https://www.heisener.com E-mail: salesdept@heisener.com



Request a Quote

## **Certified Quality**

Heisener's commitment to quality has shaped our processes for sourcing, testing, shipping, and every step in between. This foundation underlies each component we sell.









# **ELJ-FB391KF Specifications**

Manufacturer Part Number	ELJ-FB391KF
Manufacturer	Panasonic Electronic Components
Category	Inductors, Coils, Chokes
	Fixed Inductors
Package	1812 (4532 Metric)
Series	FB
Туре	Wirewound
Material - Core	-
Inductance	390μН
Tolerance	$\pm 10\%$
Current Rating	70mA
Current - Saturation	-
Shielding	Unshielded
DC Resistance (DCR)	19 Ohm Max
Q @ Freq	40 @ 796kHz
Frequency - Self Resonant	3.3MHz
Ratings	-
Operating Temperature	-20°C ~ 85°C
Frequency - Test	100kHz
Features	-
Mounting Type	Surface Mount
Package / Case	1812 (4532 Metric)
Supplier Device Package	1812
Size / Dimension	0.177" L x 0.126" W (4.50mm x 3.20mm)

Height - Seated (Max)	0.134" (3.40mm)
	Report errors?

### **ELJ-FB391KF Guarantees**



#### **Quality Guarantees**

We provide 90 days warranty. \*

If the items you received were not in perfect quality, we would be responsible for your refund or replacement, but the items must be returned in their original condition.



#### **Service Guarantees**

We guarantee 100% customer satisfaction.


Our experienced sales team and tech support team back our services to satisfy all our customers.

### **ELJ-FB391KF Payment Methods**





















# **ELJ-FB391KF Shipping Methods**













If you have any question about ELJ-FB391KF, please do not hesitate to contact us!

Website: https://www.heisener.com E-mail: salesdept@heisener.com