

HA24-0.5-A Information



For Reference Only

Part Number HA24-0.5-A

Manufacturer Bel Power Solutions

Category Power Supplies - External/Internal (Off-Board)

AC DC Converters

Description AC/DC CONVERTER 24V 12W

Package -

For the pricing/inventory/lead time, please contact

us

Website: https://www.heisener.com E-mail: salesdept@heisener.com



Request a Quote

Certified Quality

Heisener's commitment to quality has shaped our processes for sourcing, testing, shipping, and every step in between. This foundation underlies each component we sell.









HA24-0.5-A Specifications

| Manufacturer Part Number | HA24-0.5-A |
|--------------------------|--|
| Manufacturer | Bel Power Solutions |
| Category | Power Supplies - External/Internal (Off-Board) |
| | AC DC Converters |
| Package | - |
| Series | Linear B |
| Туре | Linear |
| Number of Outputs | 1 |
| Voltage - Input | 100, 120, 220, 230, 240 VAC |
| Voltage - Output 1 | 24V |
| Voltage - Output 2 | - |
| Voltage - Output 3 | - |
| Voltage - Output 4 | - |
| Current - Output (Max) | 500mA |
| Power (Watts) | 12W |
| Applications | ITE (Commercial) |
| Voltage - Isolation | 3kV (3000V) |
| Efficiency | 60% |
| Operating Temperature | 0°C ~ 50°C |
| Features | Adjustable Output, Remote Sense |
| Mounting Type | Chassis Mount |
| Size / Dimension | 4.87" L x 4.00" W x 2.10" H (123.7mm x 101.6mm x 53.3mm) |
| _ | Report errors? |

HA24-0.5-A Guarantees



Quality Guarantees

We provide 90 days warranty. *

If the items you received were not in perfect quality, we would be responsible for your refund or replacement, but the items must be returned in their original condition.



Service Guarantees

We guarantee 100% customer satisfaction.

Our experienced sales team and tech support team back our services to satisfy all our customers.

HA24-0.5-A Payment Methods



















HA24-0.5-A Shipping Methods













If you have any question about HA24-0.5-A, please do not hesitate to contact us!

Website: https://www.heisener.com E-mail: salesdept@heisener.com