

INA2126P Information


For Reference Only

Part Number [INA2126P](#)
Manufacturer Texas Instruments
Category Integrated Circuits (ICs)
[Linear - Amplifiers - Instrumentation, OP Amps, Buffer Amps](#)
Description IC OPAMP INSTR 200KHZ 16DIP
Package 16-DIP (0.300", 7.62mm)
 For the pricing/inventory/lead time, please contact us
 Website: <https://www.heisener.com>
 E-mail: salesdept@heisener.com


[Request a Quote](#)
Certified Quality

Heisener's commitment to quality has shaped our processes for sourcing, testing, shipping, and every step in between. This foundation underlies each component we sell.


INA2126P Specifications

| | |
|---|--|
| Manufacturer Part Number | INA2126P |
| Manufacturer | Texas Instruments |
| Category | Integrated Circuits (ICs) Linear - Amplifiers - Instrumentation, OP Amps, Buffer Amps |
| Package | 16-DIP (0.300", 7.62mm) |
| Series | - |
| Amplifier Type | Instrumentation |
| Number of Circuits | 2 |
| Output Type | - |
| Slew Rate | 0.4 V/ μ s |
| Gain Bandwidth Product | - |
| -3db Bandwidth | 200kHz |
| Current - Input Bias | 10nA |
| Voltage - Input Offset | 100 μ V |
| Current - Supply | 175 μ A |
| Current - Output / Channel | 10mA |
| Voltage - Supply, Single/Dual (\pm) | 2.7 V ~ 36 V, \pm 1.35 V ~ 18 V |
| Operating Temperature | -40°C ~ 85°C |
| Mounting Type | Through Hole |
| Package / Case | 16-DIP (0.300", 7.62mm) |
| Supplier Device Package | 16-PDIP |

[Report errors?](#)

INA2126P Guarantees



Quality Guarantees

We provide 90 days warranty. *

If the items you received were not in perfect quality, we would be responsible for your refund or replacement, but the items must be returned in their original condition.



Service Guarantees

We guarantee 100% customer satisfaction.

Our experienced sales team and tech support team back our services to satisfy all our customers.

INA2126P Payment Methods



INA2126P Shipping Methods



If you have any question about INA2126P, please do not hesitate to contact us!

Website: <https://www.heisener.com>

E-mail: salesdept@heisener.com