

**LE300S48VN Information**


For Reference Only

**Part Number** [LE300S48VN](#)  
**Manufacturer** SL Power Electronics Manufacture of Condor/Ault Brands  
**Category** Power Supplies - External/Internal (Off-Board)  
[LED Drivers](#)  
**Description** LED DRIVER CV AC/DC 48V 6.25A  
**Package** -  
 For the pricing/inventory/lead time, please contact us  
 Website: <https://www.heisener.com>  
 E-mail: [salesdept@heisener.com](mailto:salesdept@heisener.com)


[Request a Quote](#)
**Certified Quality**

Heisener's commitment to quality has shaped our processes for sourcing, testing, shipping, and every step in between. This foundation underlies each component we sell.


**LE300S48VN Specifications**

Manufacturer Part Number	<a href="#">LE300S48VN</a>
Manufacturer	SL Power Electronics Manufacture of Condor/Ault Brands
Category	Power Supplies - External/Internal (Off-Board)
	<a href="#">LED Drivers</a>
Package	-
Series	LE300S-VN
Type	Constant Voltage
Topology	AC DC Converter
Number of Outputs	1
Voltage - Input (Min)	90VAC
Voltage - Input (Max)	305VAC
Voltage - Output	48V
Current - Output (Max)	6.25A
Power (Watts)	300W
Voltage - Isolation	-
Dimming	-
Features	OCP, OTP, OVP, SCP
Ratings	IP67
Operating Temperature	-35°C ~ 70°C
Efficiency	94%
Termination Style	Wire Leads
Size / Dimension	9.88" L x 3.86" W x 1.75" H (251.0mm x 98.0mm x 44.5mm)

[Report errors?](#)

## LE300S48VN Guarantees



### Quality Guarantees

We provide 90 days warranty. \*

If the items you received were not in perfect quality, we would be responsible for your refund or replacement, but the items must be returned in their original condition.



### Service Guarantees

We guarantee 100% customer satisfaction.

Our experienced sales team and tech support team back our services to satisfy all our customers.

## LE300S48VN Payment Methods



## LE300S48VN Shipping Methods



If you have any question about LE300S48VN, please do not hesitate to contact us!

Website: <https://www.heisener.com>

E-mail: [salesdept@heisener.com](mailto:salesdept@heisener.com)