

LQW18ASR20J0ZD

LQW18ASR20J0ZD Information



| Part Number | LQW18ASR20J0ZD |
|--------------|--|
| Manufacturer | Murata |
| Category | Inductors, Coils, Chokes Fixed Inductors |
| Description | FIXED IND 200NH 200MA 1.98 OHM |
| Package | 0603 (1608 Metric) |
| | For the pricing/inventory/lead time, please contact us Website: https://www.heisener.com E-mail: salesdept@heisener.com |



Request a Quote

For Reference Only

Certified Quality

Heisener's commitment to quality has shaped our processes for sourcing, testing, shipping, and every step in between. This foundation underlies each component we sell.



LQW18ASR20J0ZD Specifications

| Manufacturer Part Number | LQW18ASR20J0ZD |
|---------------------------|---------------------------------------|
| Manufacturer | Murata |
| Category | Inductors, Coils, Chokes |
| | Fixed Inductors |
| Package | 0603 (1608 Metric) |
| Series | LQW18 |
| Туре | Wirewound |
| Material - Core | Non-Magnetic |
| Inductance | 200nH |
| Tolerance | $\pm 5\%$ |
| Current Rating | 200mA |
| Current - Saturation | - |
| Shielding | Unshielded |
| DC Resistance (DCR) | 1.98 Ohm Max |
| Q @ Freq | 25 @ 100MHz |
| Frequency - Self Resonant | 900MHz |
| Ratings | AEC-Q200 |
| Operating Temperature | -55°C ~ 125°C |
| Frequency - Test | 100MHz |
| Features | - |
| Mounting Type | Surface Mount |
| Package / Case | 0603 (1608 Metric) |
| Supplier Device Package | 0603 (1608 Metric) |
| Size / Dimension | 0.063" L x 0.031" W (1.60mm x 0.80mm) |
| | |

0.039" (1.00mm)

LQW18ASR20J0ZD Guarantees



Website: https://www.heisener.com

E-mail: salesdept@heisener.com