

MAX9938FELT+T Information


For Reference Only

Part Number [MAX9938FELT+T](#)
Manufacturer Maxim Integrated
Category Integrated Circuits (ICs)
[Linear - Amplifiers - Instrumentation, OP Amps, Buffer Amps](#)
Description IC OPAMP CURR SENSE 60KHZ 6UDFN
Package 6-WDFN
 For the pricing/inventory/lead time, please contact us
 Website: <https://www.heisener.com>
 E-mail: salesdept@heisener.com


[Request a Quote](#)
Certified Quality

Heisener's commitment to quality has shaped our processes for sourcing, testing, shipping, and every step in between. This foundation underlies each component we sell.


MAX9938FELT+T Specifications

| | |
|-----------------------------------|--|
| Manufacturer Part Number | MAX9938FELT+T |
| Manufacturer | Maxim Integrated |
| Category | Integrated Circuits (ICs) Linear - Amplifiers - Instrumentation, OP Amps, Buffer Amps |
| Package | 6-WDFN |
| Series | - |
| Amplifier Type | Current Sense |
| Number of Circuits | 1 |
| Output Type | - |
| Slew Rate | - |
| Gain Bandwidth Product | - |
| -3db Bandwidth | 60kHz |
| Current - Input Bias | - |
| Voltage - Input Offset | 100µV |
| Current - Supply | 1.1µA |
| Current - Output / Channel | - |
| Voltage - Supply, Single/Dual (±) | 1.6 V ~ 28 V |
| Operating Temperature | -40°C ~ 85°C |
| Mounting Type | Surface Mount |
| Package / Case | 6-WDFN |
| Supplier Device Package | 6-µDFN(2x2) |

[Report errors?](#)

MAX9938FELT+T Guarantees



Quality Guarantees

We provide 90 days warranty. *

If the items you received were not in perfect quality, we would be responsible for your refund or replacement, but the items must be returned in their original condition.



Service Guarantees

We guarantee 100% customer satisfaction.

Our experienced sales team and tech support team back our services to satisfy all our customers.

MAX9938FELT+T Payment Methods



MAX9938FELT+T Shipping Methods



If you have any question about MAX9938FELT+T, please do not hesitate to contact us!

Website: <https://www.heisener.com>

E-mail: salesdept@heisener.com