

MBRB2535CTL Information


For Reference Only

Part Number [MBRB2535CTL](#)
Manufacturer ON Semiconductor
Category Discrete Semiconductor Products
 [Diodes - Rectifiers - Arrays](#)
Description DIODE ARRAY SCHOTTKY 35V D2PAK
Package TO-263-3, D2Pak (2 Leads + Tab), TO-263AB
 For the pricing/inventory/lead time, please contact us
 Website: <https://www.heisener.com>
 E-mail: salesdept@heisener.com


[Request a Quote](#)
Certified Quality

Heisener's commitment to quality has shaped our processes for sourcing, testing, shipping, and every step in between. This foundation underlies each component we sell.


MBRB2535CTL Specifications

Manufacturer Part Number	MBRB2535CTL
Manufacturer	ON Semiconductor
Category	Discrete Semiconductor Products Diodes - Rectifiers - Arrays
Package	TO-263-3, D2Pak (2 Leads + Tab), TO-263AB
Series	SWITCHMODE?
Diode Configuration	1 Pair Common Cathode
Diode Type	Schottky
Voltage - DC Reverse (Vr) (Max)	35V
Current - Average Rectified (Io) (per Diode)	12.5A
Voltage - Forward (Vf) (Max) @ If	470mV @ 12.5A
Speed	Fast Recovery =< 500ns, > 200mA (Io)
Reverse Recovery Time (trr)	-
Current - Reverse Leakage @ Vr	10mA @ 35V
Operating Temperature - Junction	-65°C ~ 125°C
Mounting Type	Surface Mount
Package / Case	TO-263-3, D2Pak (2 Leads + Tab), TO-263AB
Supplier Device Package	D2PAK-3

[Report errors?](#)

MBRB2535CTL Guarantees



Quality Guarantees

We provide 90 days warranty. *

If the items you received were not in perfect quality, we would be responsible for your refund or replacement, but the items must be returned in their original condition.



Service Guarantees

We guarantee 100% customer satisfaction.

Our experienced sales team and tech support team back our services to satisfy all our customers.

MBRB2535CTL Payment Methods



MBRB2535CTL Shipping Methods



If you have any question about MBRB2535CTL, please do not hesitate to contact us!

Website: <https://www.heisener.com>

E-mail: salesdept@heisener.com