

MBRB3030CTL Information


For Reference Only

Part Number [MBRB3030CTL](#)
Manufacturer ON Semiconductor
Category Discrete Semiconductor Products
[Diodes - Rectifiers - Arrays](#)
Description DIODE ARRAY SCHOTTKY 30V D2PAK
Package TO-263-3, D2Pak (2 Leads + Tab), TO-263AB
 For the pricing/inventory/lead time, please contact us
 Website: <https://www.heisener.com>
 E-mail: salesdept@heisener.com


[Request a Quote](#)
Certified Quality

Heisener's commitment to quality has shaped our processes for sourcing, testing, shipping, and every step in between. This foundation underlies each component we sell.


MBRB3030CTL Specifications

Manufacturer Part Number	MBRB3030CTL
Manufacturer	ON Semiconductor
Category	Discrete Semiconductor Products Diodes - Rectifiers - Arrays
Package	TO-263-3, D2Pak (2 Leads + Tab), TO-263AB
Series	SWITCHMODE?
Diode Configuration	1 Pair Common Cathode
Diode Type	Schottky
Voltage - DC Reverse (Vr) (Max)	30V
Current - Average Rectified (Io) (per Diode)	15A
Voltage - Forward (Vf) (Max) @ If	440mV @ 15A
Speed	Fast Recovery =< 500ns, > 200mA (Io)
Reverse Recovery Time (trr)	-
Current - Reverse Leakage @ Vr	2mA @ 30V
Operating Temperature - Junction	-55°C ~ 125°C
Mounting Type	Surface Mount
Package / Case	TO-263-3, D2Pak (2 Leads + Tab), TO-263AB
Supplier Device Package	D2PAK-3

[Report errors?](#)

MBRB3030CTL Guarantees



Quality Guarantees

We provide 90 days warranty. *

If the items you received were not in perfect quality, we would be responsible for your refund or replacement, but the items must be returned in their original condition.



Service Guarantees

We guarantee 100% customer satisfaction.

Our experienced sales team and tech support team back our services to satisfy all our customers.

MBRB3030CTL Payment Methods



MBRB3030CTL Shipping Methods



If you have any question about MBRB3030CTL, please do not hesitate to contact us!

Website: <https://www.heisener.com>

E-mail: salesdept@heisener.com