



MMBD1501A_D87Z Information

Part Number MMBD1501A_D87Z

Manufacturer Fairchild/ON Semiconductor

Category Discrete Semiconductor Products
Diodes - Rectifiers - Single

Description DIODE GEN PURP 200V 200MA SOT23

Package TO-236-3, SC-59, SOT-23-3

For the pricing/inventory/lead time, please contact

us

For Reference Only

Website: https://www.heisener.com
E-mail: salesdept@heisener.com



Request a Quote

Certified Quality

Heisener's commitment to quality has shaped our processes for sourcing, testing, shipping, and every step in between. This foundation underlies each component we sell.









MMBD1501A_D87Z Specifications

Manufacturer Part NumberMMBD1501A_D87ZManufacturerFairchild/ON SemiconductorCategoryDiscrete Semiconductor ProductsDiodes - Rectifiers - SinglePackageTO-236-3, SC-59, SOT-23-3Series-Diode TypeStandardVoltage - DC Reverse (Vr) (Max)200VCurrent - Average Rectified (Io)200mAVoltage - Forward (Vf) (Max) @ If1.1V @ 200mASpeedSmall Signal =< 200mA (Io), Any SpeedReverse Recovery Time (trr)-Current - Reverse Leakage @ Vr10nA @ 180V
Category Discrete Semiconductor Products Diodes - Rectifiers - Single Package TO-236-3, SC-59, SOT-23-3 Series - Diode Type Standard Voltage - DC Reverse (Vr) (Max) Current - Average Rectified (Io) Voltage - Forward (Vf) (Max) @ If Speed Reverse Recovery Time (trr) Discrete Semiconductor Products Diodes - Rectifiers - Single TO-236-3, SC-59, SOT-23-3 Series - 1.1V @ 200TA Speed Small Signal =< 200mA (Io), Any Speed
Diodes - Rectifiers - Single Package TO-236-3, SC-59, SOT-23-3 Series - Diode Type Standard Voltage - DC Reverse (Vr) (Max) Current - Average Rectified (Io) 200mA Voltage - Forward (Vf) (Max) @ If 1.1V @ 200mA Speed Small Signal =< 200mA (Io), Any Speed Reverse Recovery Time (trr) -
Package TO-236-3, SC-59, SOT-23-3 Series - Diode Type Standard Voltage - DC Reverse (Vr) (Max) 200V Current - Average Rectified (Io) 200mA Voltage - Forward (Vf) (Max) @ If 1.1V @ 200mA Speed Small Signal =< 200mA (Io), Any Speed Reverse Recovery Time (trr) -
Series - Diode Type Standard Voltage - DC Reverse (Vr) (Max) 200V Current - Average Rectified (Io) 200mA Voltage - Forward (Vf) (Max) @ If 1.1V @ 200mA Speed Small Signal =< 200mA (Io), Any Speed Reverse Recovery Time (trr) -
Diode Type Standard Voltage - DC Reverse (Vr) (Max) Current - Average Rectified (Io) Voltage - Forward (Vf) (Max) @ If 1.1V @ 200mA Speed Small Signal =< 200mA (Io), Any Speed Reverse Recovery Time (trr) -
Voltage - DC Reverse (Vr) (Max) Current - Average Rectified (Io) Voltage - Forward (Vf) (Max) @ If 1.1V @ 200mA Speed Small Signal =< 200mA (Io), Any Speed Reverse Recovery Time (trr)
Current - Average Rectified (Io) Voltage - Forward (Vf) (Max) @ If Speed Small Signal =< 200mA (Io), Any Speed Reverse Recovery Time (trr) -
Voltage - Forward (Vf) (Max) @ If Speed Small Signal =< 200mA (Io), Any Speed Reverse Recovery Time (trr) -
Speed Small Signal =< 200mA (Io), Any Speed Reverse Recovery Time (trr) -
Reverse Recovery Time (trr) -
Current - Reverse Leakage @ Vr 10nA @ 180V
Capacitance @ Vr, F 4pF @ 0V, 1MHz
Mounting Type Surface Mount
Package / Case TO-236-3, SC-59, SOT-23-3
Supplier Device Package SOT-23-3
Operating Temperature - Junction 150°C (Max)
Report errors?

MMBD1501A_D87Z Guarantees



Quality Guarantees

We provide 90 days warranty. *

If the items you received were not in perfect quality, we would be responsible for your refund or replacement, but the items must be returned in their original condition.



Service Guarantees

We guarantee 100% customer satisfaction.

Our experienced sales team and tech support team back our services to satisfy all our customers.

MMBD1501A_D87Z Payment Methods



















MMBD1501A_D87Z Shipping Methods













If you have any question about MMBD1501A_D87Z, please do not hesitate to contact us!

Website: https://www.heisener.com E-mail: salesdept@heisener.com