

NLP40-7610

NLP40-7610 Information

	Part Number Manufacturer Category Description Package	Artesyn Embedded Technologies Power Supplies - External/Internal (Off-Board) AC DC Converters AC/DC CONVERTER 5V +/-15V 40W - For the pricing/inventory/lead time, please contact	
For Reference Only		us Website: https://www.heisener.com E-mail: salesdept@heisener.com	Request a Quote

Certified Quality

Heisener's commitment to quality has shaped our processes for sourcing, testing, shipping, and every step in between. This foundation underlies each component we sell.



NLP40-7610 Specifications

Manufacturer Part Number	NLP40-7610		
Manufacturer	Artesyn Embedded Technologies		
Category	Power Supplies - External/Internal (Off-Board)		
	AC DC Converters		
Package	-		
Series	NLP40		
Туре	Open Frame		
Number of Outputs	3		
Voltage - Input	90 ~ 264 VAC		
Voltage - Output 1	5V		
Voltage - Output 2	15V		
Voltage - Output 3	-15V		
Voltage - Output 4	-		
Current - Output (Max)	4A, 1.6A, 200mA		
Power (Watts)	40W (50W Forced Air)		
Applications	ITE (Commercial)		
Voltage - Isolation	3kV (3000V)		
Efficiency	75%		
Operating Temperature	0°C ~ 70°C		
Features	DC Input Capable, Universal Input		
Mounting Type	Chassis Mount		
Size / Dimension	4.25" L x 2.50" W x 1.15" H (108.0mm x 63.5mm x 29.2mm)		
		Report errors?	

NLP40-7610 Guarantees



Quality Guarantees

We provide 90 days warranty. * If the items you received were not in perfect quality, we would be responsible for your refund or replacement, but the items must be returned in their original condition.

SERVICE EUARANTEE

Service Guarantees

We guarantee 100% customer satisfaction. Our experienced sales team and tech support team back our services to satisfy all our customers.

NLP40-7610 Payment Methods WIRE transfer PayPal WIRE review meany for better MoneyGram Alippy INA WAR WIRE NLP40-7610 Shipping Methods FREEX. W TOND TONS

If you have any question about NLP40-7610, please do not hesitate to contact us! Website: https://www.heisener.com E-mail: salesdept@heisener.com