

PDA241-SRT01-504B0 Information


For Reference Only

Part Number [PDA241-SRT01-504B0](#)
Manufacturer Bourns Inc.
Category Potentiometers, Variable Resistors
[Rotary Potentiometers, Rheostats](#)
Description POT 500K OHM 1/2W CARBON LINEAR
Package -
 For the pricing/inventory/lead time, please contact us
 Website: <https://www.heisener.com>
 E-mail: salesdept@heisener.com


[Request a Quote](#)
Certified Quality

Heisener's commitment to quality has shaped our processes for sourcing, testing, shipping, and every step in between. This foundation underlies each component we sell.


PDA241-SRT01-504B0 Specifications

| | |
|--------------------------|--|
| Manufacturer Part Number | PDA241-SRT01-504B0 |
| Manufacturer | Bourns Inc. |
| Category | Potentiometers, Variable Resistors Rotary Potentiometers, Rheostats |
| Package | - |
| Series | Pro Audio PDA24 |
| Taper | Linear |
| Resistance (Ohms) | 500k |
| Tolerance | ±15% |
| Number of Gangs | 1 |
| Built in Switch | None |
| Power (Watts) | 0.5W, 1/2W |
| Temperature Coefficient | - |
| Number of Turns | 1 |
| Rotation | 300° |
| Adjustment Type | User Defined |
| Resistive Material | Carbon |
| Termination Style | Solder Lug |
| Actuator Type | Knurled and Slotted |
| Actuator Length | 0.748" (19.00mm) |
| Actuator Diameter | 0.236" (6.00mm) |
| Bushing Thread | 3/8-32 |
| Mounting Type | Panel Mount |
| | Report errors? |

PDA241-SRT01-504B0 Guarantees



Quality Guarantees

We provide 90 days warranty. *

If the items you received were not in perfect quality, we would be responsible for your refund or replacement, but the items must be returned in their original condition.



Service Guarantees

We guarantee 100% customer satisfaction.

Our experienced sales team and tech support team back our services to satisfy all our customers.

PDA241-SRT01-504B0 Payment Methods



PDA241-SRT01-504B0 Shipping Methods



If you have any question about PDA241-SRT01-504B0, please do not hesitate to contact us!

Website: <https://www.heisener.com>

E-mail: salesdept@heisener.com