

PWR263S-35-56R0J Information


For Reference Only

Part Number [PWR263S-35-56R0J](#)
Manufacturer Bourns Inc.
Category Resistors
[Chip Resistor - Surface Mount](#)
Description RES SMD 56 OHM 5% 35W D2PAK
Package TO-263-3, D2Pak (2 Leads + Tab), TO-263AB
 For the pricing/inventory/lead time, please contact us
 Website: <https://www.heisener.com>
 E-mail: salesdept@heisener.com



[Request a Quote](#)

Certified Quality

Heisener's commitment to quality has shaped our processes for sourcing, testing, shipping, and every step in between. This foundation underlies each component we sell.


PWR263S-35-56R0J Specifications

| | |
|--------------------------|--|
| Manufacturer Part Number | PWR263S-35-56R0J |
| Manufacturer | Bourns Inc. |
| Category | Resistors Chip Resistor - Surface Mount |
| Package | TO-263-3, D2Pak (2 Leads + Tab), TO-263AB |
| Series | PWR263S-35 |
| Resistance | 56 Ohms |
| Tolerance | ±5% |
| Power (Watts) | 35W |
| Composition | Thick Film |
| Features | Automotive AEC-Q200, Current Sense, Pulse Withstanding |
| Temperature Coefficient | ±100ppm/°C |
| Operating Temperature | -55°C ~ 155°C |
| Package / Case | TO-263-3, D2Pak (2 Leads + Tab), TO-263AB |
| Supplier Device Package | D2PAK |
| Size / Dimension | 0.398" L x 0.409" W (10.10mm x 10.40mm) |
| Height - Seated (Max) | 0.192" (4.88mm) |
| Number of Terminations | 2 |
| Failure Rate | - |

[Report errors?](#)

PWR263S-35-56R0J Guarantees



Quality Guarantees

We provide 90 days warranty. *

If the items you received were not in perfect quality, we would be responsible for your refund or replacement, but the items must be returned in their original condition.



Service Guarantees

We guarantee 100% customer satisfaction.

Our experienced sales team and tech support team back our services to satisfy all our customers.

PWR263S-35-56R0J Payment Methods



PWR263S-35-56R0J Shipping Methods



If you have any question about PWR263S-35-56R0J, please do not hesitate to contact us!

Website: <https://www.heisener.com>

E-mail: salesdept@heisener.com