

VI-22Z-IX-F3 Information



For Reference Only

Part Number VI-22Z-IX-F3
Manufacturer Vicor Corporation

Category Power Supplies - Board Mount

DC DC Converters

Description CONVERTER MOD DC/DC 2V 30W

Package Full Brick

For the pricing/inventory/lead time, please contact

us

Website: https://www.heisener.com E-mail: salesdept@heisener.com



Request a Quote

Certified Quality

Heisener's commitment to quality has shaped our processes for sourcing, testing, shipping, and every step in between. This foundation underlies each component we sell.









VI-22Z-IX-F3 Specifications

Manufacturer Part Number Manufacturer Vicor Corporation Category Power Supplies - Board Mount DC DC Converters Package Full Brick Series VI-200 Type Isolated Module Number of Outputs Voltage - Input (Min) Voltage - Input (Max) Voltage - Output 1 Voltage - Output 2 Voltage - Output 3 Voltage - Output 4 Current - Output (Max) 15A	
Category Power Supplies - Board Mount DC DC Converters Package Full Brick Series VI-200 Type Isolated Module Number of Outputs 1 Voltage - Input (Min) Voltage - Input (Max) Voltage - Output 1 2V Voltage - Output 2 Voltage - Output 3 Voltage - Output 4 Current - Output (Max) 15A	
Package Full Brick Series VI-200 Type Isolated Module Number of Outputs 1 Voltage - Input (Min) 21V Voltage - Input (Max) 56V Voltage - Output 1 2V Voltage - Output 2 - Voltage - Output 3 - Voltage - Output 4 - Current - Output (Max) 15A	
Package Series VI-200 Type Isolated Module Number of Outputs 1 Voltage - Input (Min) Voltage - Input (Max) Voltage - Output 1 Voltage - Output 2 Voltage - Output 3 Voltage - Output 4 Current - Output (Max) Full Brick VI-200 Isolated Module 21V Voltage - Input (Min) 21V 21V - Voltage - Output 1 22V Voltage - Output 2 - Toutput 3 - Toutput 4 - Toutput (Max) 15A	
Series VI-200 Type Isolated Module Number of Outputs 1 Voltage - Input (Min) 21V Voltage - Input (Max) 56V Voltage - Output 1 2V Voltage - Output 2 - Voltage - Output 3 - Voltage - Output 4 - Current - Output (Max) 15A	
Type Isolated Module Number of Outputs 1 Voltage - Input (Min) 21V Voltage - Input (Max) 56V Voltage - Output 1 2V Voltage - Output 2 - Voltage - Output 3 - Voltage - Output 4 - Current - Output (Max) 15A	
Number of Outputs Voltage - Input (Min) Voltage - Input (Max) Solv Voltage - Output 1 Voltage - Output 2 Voltage - Output 3 Voltage - Output 4 Current - Output (Max) 1 21V 2V	
Voltage - Input (Min) Voltage - Input (Max) 56V Voltage - Output 1 2V Voltage - Output 2 Voltage - Output 3 Voltage - Output 4 Current - Output (Max) 15A	
Voltage - Input (Max) Voltage - Output 1 Voltage - Output 2 Voltage - Output 3 Voltage - Output 4 Current - Output (Max) 56V 2V	
Voltage - Output 1 2V Voltage - Output 2 - Voltage - Output 3 - Voltage - Output 4 - Current - Output (Max) 15A	
Voltage - Output 2 - Voltage - Output 3 - Voltage - Output 4 - Current - Output (Max) 15A	
Voltage - Output 3 - Voltage - Output 4 - Current - Output (Max) 15A	
Voltage - Output 4 - Current - Output (Max) 15A	
Current - Output (Max) 15A	
• ' '	
Power (Watts) 30W	
Voltage - Isolation 3kV (3000V)	
Applications ITE (Commercial)	
Features OCP, OTP, OVP, SCP	
Operating Temperature $-40^{\circ}\text{C} \sim 85^{\circ}\text{C}$	
Efficiency 90%	
Mounting Type Through Hole	
Package / Case Full Brick	
Size / Dimension 4.60" L x 1.86" W x 0.79" H (116.8mm x 4	7.2mm x 20.1mm)

Supplier Device Package	-
Control Features	-
	Report errors?

VI-22Z-IX-F3 Guarantees



Quality Guarantees

We provide 90 days warranty. *

If the items you received were not in perfect quality, we would be responsible for your refund or replacement, but the items must be returned in their original condition.



Service Guarantees

We guarantee 100% customer satisfaction.

Our experienced sales team and tech support team back our services to satisfy all our customers.

VI-22Z-IX-F3 Payment Methods



















VI-22Z-IX-F3 Shipping Methods













If you have any question about VI-22Z-IX-F3, please do not hesitate to contact us!

Website: https://www.heisener.com E-mail: salesdept@heisener.com