

VI-25W-MW-S

a Quote

VI-25W-MW-S Information

| The second second | Part Number | VI-25W-MW-S | |
|--------------------|--------------|---|---------|
| | Manufacturer | Vicor Corporation | |
| | Category | Power Supplies - Board Mount DC DC Converters | 840 |
| | Description | CONVERTER MOD DC/DC 5.5V 100W | - 9° SH |
| | Package | Full Brick | - 1 |
| | | For the pricing/inventory/lead time, please contact us | ER |
| For Reference Only | | Website: https://www.heisener.com E-mail: salesdept@heisener.com | Request |

Certified Quality

Heisener's commitment to quality has shaped our processes for sourcing, testing, shipping, and every step in between. This foundation underlies each component we sell.



VI-25W-MW-S Specifications

| Manufacturer Part Number | VI-25W-MW-S | | | |
|--------------------------|---|--|--|--|
| Manufacturer | Vicor Corporation | | | |
| Category | Power Supplies - Board Mount | | | |
| | DC DC Converters | | | |
| Package | Full Brick | | | |
| Series | VI-200 | | | |
| Туре | Isolated Module | | | |
| Number of Outputs | 1 | | | |
| Voltage - Input (Min) | 100V | | | |
| Voltage - Input (Max) | 200V | | | |
| Voltage - Output 1 | 5.5V | | | |
| Voltage - Output 2 | - | | | |
| Voltage - Output 3 | - | | | |
| Voltage - Output 4 | - | | | |
| Current - Output (Max) | 18.18A | | | |
| Power (Watts) | 100W | | | |
| Voltage - Isolation | 3kV (3000V) | | | |
| Applications | ITE (Commercial) | | | |
| Features | OCP, OTP, OVP, SCP | | | |
| Operating Temperature | -55°C ~ 85°C | | | |
| Efficiency | 90% | | | |
| Mounting Type | Through Hole | | | |
| Package / Case | Full Brick | | | |
| Size / Dimension | 4.60" L x 1.80" W x 0.52" H (116.8mm x 45.7mm x 13.2mm) | | | |
| | | | | |

| Supplier Device Package | - | | |
|-------------------------|---|--|----------------|
| Control Features | - | | |
| | | | Report errors? |

VI-25W-MW-S Guarantees



If you have any question about VI-25W-MW-S, please do not hesitate to contact us! Website: https://www.heisener.com E-mail: salesdept@heisener.com