



## **VI-B1P-EX-S Information**

Heisener.com

Part Number VI-B1P-EX-S
Manufacturer Vicor Corporation

**Category** Power Supplies - Board Mount

DC DC Converters

**Description** CONVERTER MOD DC/DC 13.8V 75W


Package Full Brick


For the pricing/inventory/lead time, please contact

us

For Reference Only

Website: https://www.heisener.com
E-mail: salesdept@heisener.com





Heisener's commitment to quality has shaped our processes for sourcing, testing, shipping, and every step in between. This foundation underlies each component we sell.









VI-R1P-EX-S	<b>Specifications</b>
A1-D11 -FV-9	Specifications

Manufacturer Part Number	VI-B1P-EX-S
Manufacturer Manufacturer	
	Vicor Corporation
Category	Power Supplies - Board Mount
	DC DC Converters
Package	Full Brick
Series	VI-200
Туре	Isolated Module
Number of Outputs	1
Voltage - Input (Min)	21V
Voltage - Input (Max)	32V
Voltage - Output 1	13.8V
Voltage - Output 2	-
Voltage - Output 3	-
Voltage - Output 4	-
Current - Output (Max)	5.43A
Power (Watts)	75W
Voltage - Isolation	3kV (3000V)
Applications	ITE (Commercial)
Features	OCP, OTP, OVP, SCP
Operating Temperature	-10°C ~ 85°C
Efficiency	88%
Mounting Type	Through Hole
Package / Case	Full Brick
Size / Dimension	4.60" L x 1.80" W x 0.52" H (116.8mm x 45.7mm x 13.2mm)

Supplier Device Package	-
Control Features	-
	Report errors?

### **VI-B1P-EX-S Guarantees**



### **Quality Guarantees**

We provide 90 days warranty. \*

If the items you received were not in perfect quality, we would be responsible for your refund or replacement, but the items must be returned in their original condition.



#### **Service Guarantees**

We guarantee 100% customer satisfaction.

Our experienced sales team and tech support team back our services to satisfy all our customers.

# **VI-B1P-EX-S Payment Methods**


































If you have any question about VI-B1P-EX-S, please do not hesitate to contact us!

Website: https://www.heisener.com E-mail: salesdept@heisener.com