



VI-BNL-CX-F1 Information

Heisener.com

Part Number VI-BNL-CX-F1
Manufacturer Vicor Corporation

Category Power Supplies - Board Mount

DC DC Converters

Description CONVERTER MOD DC/DC 28V 75W

Package Full Brick


For the pricing/inventory/lead time, please contact

us

For Reference Only

Website: https://www.heisener.com
E-mail: salesdept@heisener.com

Request a Quote



Heisener's commitment to quality has shaped our processes for sourcing, testing, shipping, and every step in between. This foundation underlies each component we sell.









VI-BNL-CX-F1 Specifications

| Manufacturer Part Number Manufacturer Vicor Corporat Vicor Corporat Vicor Corporat Power Supplies DC DC Conver Package Full Brick VI-200 Type Isolated Modul Number of Outputs Voltage - Input (Min) Voltage - Input (Max) Voltage - Output 1 Voltage - Output 2 | cion s - Board Mount |
|--|---|
| Category Power Supplies DC DC Conver Package Full Brick Series VI-200 Type Isolated Modul Number of Outputs 1 Voltage - Input (Min) Voltage - Input (Max) Voltage - Output 1 28V | s - Board Mount |
| Package Full Brick Series VI-200 Type Isolated Modul Number of Outputs 1 Voltage - Input (Min) 36V Voltage - Input (Max) 76V Voltage - Output 1 28V | |
| Package Full Brick Series VI-200 Type Isolated Modul Number of Outputs 1 Voltage - Input (Min) 36V Voltage - Input (Max) 76V Voltage - Output 1 28V | rters |
| Series VI-200 Type Isolated Modul Number of Outputs 1 Voltage - Input (Min) 36V Voltage - Input (Max) 76V Voltage - Output 1 28V | |
| Type Isolated Modul Number of Outputs 1 Voltage - Input (Min) 36V Voltage - Input (Max) 76V Voltage - Output 1 28V | |
| Number of Outputs Voltage - Input (Min) Voltage - Input (Max) Voltage - Output 1 28V | |
| Voltage - Input (Min) 36V Voltage - Input (Max) 76V Voltage - Output 1 28V | e |
| Voltage - Input (Max) 76V Voltage - Output 1 28V | |
| Voltage - Output 1 28V | |
| - | |
| Voltage - Output 2 | |
| | |
| Voltage - Output 3 | |
| Voltage - Output 4 | |
| Current - Output (Max) 2.68A | |
| Power (Watts) 75W | |
| Voltage - Isolation 3kV (3000V) | |
| Applications ITE (Commerc | ial) |
| Features OCP, OTP, OV | P, SCP |
| Operating Temperature $-25^{\circ}\text{C} \sim 85^{\circ}\text{C}$ | |
| Efficiency 90% | |
| Mounting Type Through Hole | |
| Package / Case Full Brick | |
| Size / Dimension 4.60" L x 1.86" | |
| | ' W x 0.79" H (116.8mm x 47.2mm x 20.1mm) |

| Supplier Device Package | - |
|-------------------------|----------------|
| Control Features | - |
| | Report errors? |

VI-BNL-CX-F1 Guarantees



Quality Guarantees

We provide 90 days warranty. *

If the items you received were not in perfect quality, we would be responsible for your refund or replacement, but the items must be returned in their original condition.



Service Guarantees

We guarantee 100% customer satisfaction.

Our experienced sales team and tech support team back our services to satisfy all our customers.

VI-BNL-CX-F1 Payment Methods



















VI-BNL-CX-F1 Shipping Methods













If you have any question about VI-BNL-CX-F1, please do not hesitate to contact us!

Website: https://www.heisener.com E-mail: salesdept@heisener.com