

Heisener.com

### Y4065 Information

Part Number Y4065

Manufacturer Laird Technologies IAS

**Category** RF/IF and RFID

**RF** Antennas

**Description** ANT YAGI 5ELEM 406-430MHZ GOLD

Package -

For the pricing/inventory/lead time, please contact

us

For Reference Only

Website: https://www.heisener.com
E-mail: salesdept@heisener.com

Request a Quote



## **Certified Quality**

Heisener's commitment to quality has shaped our processes for sourcing, testing, shipping, and every step in between. This foundation underlies each component we sell.









# **Y4065 Specifications**

Manufacturer Part NumberY4065ManufacturerLaird Technologies IASCategoryRF/IF and RFIDRF AntennasPackage-Series-Frequency GroupUHF (300 MHz ~ 1 GHz)Frequency (Center/Band)418MHzFrequency Range406MHz ~ 430MHzAntenna TypeYagi, 5-ElementNumber of Bands1VSWR1.5Return Loss-Gain9.2dBd	-	
Category  RF/IF and RFID  RF Antennas  Package  - Series  - Frequency Group  UHF (300 MHz ~ 1 GHz)  Frequency (Center/Band)  Frequency Range  406MHz ~ 430MHz  Antenna Type  Yagi, 5-Element  Number of Bands  1  VSWR  Return Loss  -	Manufacturer Part Number	Y4065
RF Antennas         Package       -         Series       -         Frequency Group       UHF (300 MHz ~ 1 GHz)         Frequency (Center/Band)       418MHz         Frequency Range       406MHz ~ 430MHz         Antenna Type       Yagi, 5-Element         Number of Bands       1         VSWR       1.5         Return Loss       -	Manufacturer	Laird Technologies IAS
Package - Series - Frequency Group UHF (300 MHz ~ 1 GHz) Frequency (Center/Band) 418MHz Frequency Range 406MHz ~ 430MHz Antenna Type Yagi, 5-Element Number of Bands 1 VSWR 1.5 Return Loss -	Category	RF/IF and RFID
Series - Frequency Group UHF (300 MHz ~ 1 GHz) Frequency (Center/Band) 418MHz Frequency Range 406MHz ~ 430MHz Antenna Type Yagi, 5-Element Number of Bands 1 VSWR 1.5 Return Loss -		RF Antennas
Frequency Group  Frequency (Center/Band)  Frequency Range  406MHz ~ 430MHz  Antenna Type  Yagi, 5-Element  Number of Bands  1  VSWR  1.5  Return Loss	Package	-
Frequency (Center/Band)  Frequency Range  406MHz ~ 430MHz  Antenna Type  Yagi, 5-Element  Number of Bands  1  VSWR  1.5  Return Loss  -	Series	-
Frequency Range 406MHz ~ 430MHz  Antenna Type Yagi, 5-Element  Number of Bands 1  VSWR 1.5  Return Loss -	Frequency Group	UHF (300 MHz ~ 1 GHz)
Antenna Type Yagi, 5-Element  Number of Bands 1  VSWR 1.5  Return Loss -	Frequency (Center/Band)	418MHz
Number of Bands1VSWR1.5Return Loss-	Frequency Range	406MHz ~ 430MHz
VSWR 1.5 Return Loss -	Antenna Type	Yagi, 5-Element
Return Loss -	Number of Bands	1
	VSWR	1.5
Gain 9.2dBd	Return Loss	-
	Gain	9.2dBd
Power - Max	Power - Max	-
Features -	Features	-
Termination Connector, N Female	Termination	Connector, N Female
Ingress Protection -	Ingress Protection	-
Mounting Type Bracket Mount	Mounting Type	Bracket Mount
Height (Max) 37.000" (939.80mm)	Height (Max)	37.000" (939.80mm)
Applications -	Applications	-
Report errors		Report errors?

### Y4065 Guarantees



#### **Quality Guarantees**

We provide 90 days warranty. \*

If the items you received were not in perfect quality, we would be responsible for your refund or replacement, but the items must be returned in their original condition.



#### **Service Guarantees**

We guarantee 100% customer satisfaction.

Our experienced sales team and tech support team back our services to satisfy all our customers.

## Y4065 Payment Methods



















# Y4065 Shipping Methods













If you have any question about Y4065, please do not hesitate to contact us!

Website: https://www.heisener.com E-mail: salesdept@heisener.com